

## LED POWER SUPPLY

white | 24 V | 30W | integrated connectors

Product code: LED28030



24 V driver for LED light fixtures

### Dimming and lighting control

Appropriate lighting for any occasion is made easy with our dimming and lighting control system. You can easily change the lighting and ambience in your home from efficient and bright to dim and cosy by dimming your LIMENTE lights with our wireless system. You can use the same switch to adjust all the LIMENTE lights in the room, including various ceiling, panel and profile lights. The light adjusts smoothly at the same time while creating ambience for working, entertaining or any mood in between.

[Learn more from our website](#)

### Protection

#### THE FOLLOWING ITEMS ARE INCLUDED

- driver with integrated manifold
- detachable power cord with plug
- Plastic Free packaging

## LED 24V DRIVER 30W

### OVERVIEW

|                   |                        |
|-------------------|------------------------|
| PRODUCT CODE      | LED28030               |
| GTIN-CODE         | 6438400002678          |
| ELECTRICAL NUMBER | 4009738                |
| ETIM GENERAL NAME | Transformer            |
| ETIM CLASS        | LED driver EC002710    |
| ETIM GROUP        | 40 Lighting components |
| COLOUR            | White                  |
| LAMP TYPE         |                        |

### SPECIFICATIONS

|                                   |   |
|-----------------------------------|---|
| PRODUCT DIMENSIONS                | 178.0 x 51.5 x 17.0   |
| POSITION                          | On the top cabin, Inside the cabin  |
| MOUNTING METHOD                   | Surface mounting, Cable coupling  |
| COLOUR TEMPERATURE                |   |
| COLOUR RENDERING INDEX CRI        |   |
| RATED LIFE TIME                   |   |
| ENERGY EFFICIENCY CLASS           |   |
| LUMINOUS FLUX                     |   |
| EFFICIENCY                        |   |
| VOLTAGE                           | 24 V DC   |
| INGRESS PROTECTION CODE           | IP20  |
| NUMBER OF LEDS/M                  |   |
| INPUT POWER                       | -   |
| NUMBER OF SWITCHING CYCLES        |   |
| AMBIENT TEMPERATURE RANGE         | -20°C~45°C  |
| INPUT POWER CONNECTOR             | Europlug  |
| WARRANTY PERIOD (MONTHS)          | 24  |
| ADDITIONAL COVER (MONTHS)         | -   |
| INSTALLATION AND OPERATING MANUAL | <a href="https://www.limente.fi/Images/productpics/instructions/limente_driver.pdf">https://www.limente.fi/Images/productpics/instructions/limente_driver.pdf</a> |

## LED 24V DRIVER 30W

